



M8 MOTION SENSOR SETTINGS GUIDE



M8 Motion Sensor

Premise LED Inc.
82-86 Carrier Drive
Toronto, ON Canada
M9W 5R1
PREMISELED.COM

For use with:

VP2 and VPHB1 Series Vapor Proof (120-277V)

**THE M8 SENSOR CAN ALSO BE CONTROLLED VIA
RC-100 REMOTE**

Factory Default Settings:

100% detection range, 10 second hold time, 30lux daylight threshold, 30% stand-by dimming level, 60 minutes stand-by period

BEFORE YOU BEGIN

Before beginning the setup of your motion sensor, please familiarize yourself with the sensor's layout and dip switches.

Detection Range		Hold Time		Daylight Sensor		Stand-by Dim Level		Stand-by Dim Period	
1	2	3	4	5	6	7	8	9	10
↓	↓	↓	↓	↓	↓	↓	↓	↓	↓
↓	↑	↓	↑	↓	↑	↓	↑	↓	↑
↑	↓	↑	↓	↑	↓	↑	↓	↑	↓
↑	↑	↑	↑	↑	↑	↑	↑	↑	↑
20%	10S	(light sensor disable)	0%	+∞					
50%	1Min	10Lux	10%	1Min					
75%	5Min	30Lux	30%	30Min					
100%	15Min	50Lux	50%	60Min					