



Country Of Origin : China

DS710-10Z

Decora Slide Dimmer for 0-10V Power Supplies, 1200VA/1500VA Fluorescent, 10A LED, 120/277VAC

Decora Slide Preset Electro-Mechanical 0-10V Slide Dimmer for use with LED or Fluorescent Ballasts and Power Supplies, suitable for use with Class 1 or Class 2 wiring, 1200VA @ 120VAC and 1500VA @ 277VAC Fluorescent, 10A LED/Electronic Ballast 120/277VAC, 60Hz, 50mAmps maximum sinking current, single pole or 3-way control when used with 3-way switch - White, Ivory & Light Almond

- INNOVATIVE Designed for use with LED fixtures using 0-10V power supplies
- ADVANCED No power pack required for switching
- EXCEPTIONAL Superior quality and dimming performance
- FLEXIBLE Can be used in a single-pole or 3-way installation (with a 3-way switch, sold separately)

Technical Information

Product Features

Action : Rocker Switch for ON/OFF, slide bar for lighting level control

Available Colors : Ivry-I Wht-W Gry-G Blk-E Brwn-B Light Almond-T, R-Red

Color: White, Ivory, Light Almond

Frequency: 60 Hz

Load Rating: 1200VA-120VAC, 1500VA-277VAC, 10A LED 120VAC &

277VAC

Load Type: Electronic 0-10VDC

Fluorescent

Ordering Notes: Included White, Ivory

and Light Almond Color Kit

Preset: Slide bar preserves desired

lighting level

Protection: Radio/TV Filter Standards and Certifications: cCSAus. NOM

Otala Nama - Dana

Style Name : Decora

Switch Type: Single-Pole & 3-Way

Type: Dimmer Voltage: 120 VAC

Wallplate : Order Separately Warranty : 5-Year Limited

Features and Benefits

- Use only with appropriate LED 0-10V dimmable power supplies/drivers, Advance
 Transformer 120/277V
- Aesthetically pleasing design with rocker switch and slender dimmer control slide bar
- Dual voltage 120V/277V; 50mAmps maximum sink current
- Integrated linear full-range slide control for easy, precise operation
- Single pole or 3-way operation (when using 3-way switch); packaged with White,
 Ivory, and Light Almond color change kits
- Additional color change kits available in Black, Brown, Red and Gray
- Slim, compact housing fits easily into a standard wallbox and is suitable for multigang installations with other Decora products
- The slide bar location preserves the selected brightness level when the dimmer is switched OFF
- No fins for multi-gang installation

- Wired using leads, a Neutral wire is not required for operation
- Built-in radio/TV interference filter

Patents*

US9431192

*This list is provided for patent marking purposes only. A good faith effort is made to maintain the accuracy and completeness of this list. No legal inference should be drawn from the omission of a patent from this list.

SPECIFICATION SUBMITTAL

JOB NAME:	CATALOG NUMBERS:
JOB NUMBER:	

Leviton Manufacturing Co., Inc.

201 North Service Road, Melville, NY 11747

Telephone: +1-800-323-8920 \cdot FAX: +1-800-832-9538 \cdot Tech Line (8:30AM-7:30PM E.S.T. Monday-Friday): +1-800-824-3005

Leviton Manufacturing of Canada, Ltd.

165 Hymus Boulevard, Pointe Claire, Quebec H9R 1E9 · Telephone: +1-800-469-7890 · FAX: +1-800-824-3005 · www.leviton.com/canada

Leviton S. de R.L. de C.V.

Lago Tana 43, Mexico DF, Mexico CP 11290 · Tel.: (+52)55-5082-1040 · FAX: (+52)5386-1797 · www.leviton.com.mx

Visit our Website at: www.leviton.com

© 2021 Leviton Manufacturing Co., Inc. All Rights Reserved. Subject to change without notice.

Leviton has a global presence.

If you would like to know where your local Leviton office is located please go to: www.leviton.com/international/contacts/

